SCM5B38

Strain Gage Input Modules, Wide Bandwidth

Description

각 SCM5B38 스트레인 게이지 입력 모듈은 필터링, 절연, 증폭 높은 수준의 아날로그 전압 출력으로 변환되는 스트레인 게이 및 지 입력의 단일 채널을 제공합니다(그림 1). 이 전압 출력은 로직 스위치로 제어되며, 이를 통해 이러한 모듈은 외부 멀티플렉서를 필요로 하지 않고 공통 아날로그 버스를 공유할 수 있습니다. SCM5B 모듈은 Power Common, 핀 16에서 ±50V까지 플로팅 될 수 있는 완전히 절연된 컴퓨터 측 회로로 설계되었습니다. 이 완전한 절연은 출력 스위치의 적절한 작동을 위해 I/O Common과 Power Common 사이에 어떠한 연결도 필요하지 않 다는 것을 의미합니다.

원하는 경우 간단하게 출력 스위치를 계속 켤 수 있습니다.핀 22, 읽기 가능 핀을 I/O Common, 핀 19에 연결합니다. SCM5B38은 100*Ω* ~ 10K*Ω*의 공칭 저항으로 풀 브리지 또는 하프 브리지 변 환기에 인터페이스할 수 있습니다. 브리지 완성 저항의 일치 쌍 (+10V 여기에서 1mV까지)을 사용하면 저렴한 하프 브리지 또는

쿼터 브리지 변환기를 사용할 수 있습니다(그림 2,3,4).

10KHz 대역폭은 진동 분석과 같은 고속 프로세스의 측정을 허용 합니다.

스트레인 게이지 여기는 매우 안정적인 10V 또는 3.333V 소스에 의해 모듈에서 제공됩니다. 여기 전원은 완전히 절연되어 있어 증 폭기 입력이 여기 전압의 전체 범위에서 작동할 수 있습니다. 이 기능은 실제 응용 프로그램에서 상당한 유연성을 제공합니다 2mV/V. 3mV/V 또는 10mV/V의 풀 스케일 감도가 표준으로 제공 됩니다. 10V 여기에서 ±20mV, ±30mV 또는 ±100mV 전체 범 위 입력 범위가 발생하여 ±5V 전체 범위 출력을 생성합니다. 입력 신호는 절연 장벽의 필드 측에 있는 광대역 전치 증폭기를 통해 처리됩니다. 증폭 후 입력 신호는 독점 초퍼 회로에 의해 잘 립니다. 절연은 공통 모드 스파이크 또는 서지의 전송을 억제하는 독점 기술을 다시 사용하여 변압기 커플링에 의해 제공됩니다. 모 듈은 +5VDC, ± 5%에서 전원이 공급됩니다.

SCM5B

Features

- Interfaces to 100Ω Thru $10k\Omega$, Full-Bridge, Half-Bridge, or Quarter-Bridge Strain Gages
- High-Level Voltage Output
- 1500Vrms Transformer Isolation
- ANSI/IEEE C37.90.1 Transient Protection
- Input Protected to 240VAC Continuous
- Fully Isolated Excitation Supply
- 100dB CMR
- 10kHz Signal Bandwidth
- ±0.03% Accuracy
- ±0.01% Linearity
- ±1µV/°C Drift
- CSA C/US Certified
- CE and ATEX Compliant
- Mix and Match SCM5B Types on Backpanel

SCM5B38 모듈의 특수 입력 회로는 신호 입력 과 최대 240VAC의 절연 인가전압 공급을 보호 합니다.



Figure 1: SCM5B38 Blok Diagram

For information call 800-444-7644

©1995-2017 Dataforth Corporation, All Rights Reserved ISO9001:2008-Registered QMS

Isolated Analog Signal Conditioning Products

SCM5B

Specifications Typical* at T. = +25°C and +5VDC power

opcomoutions Typical	at 1 _A = 125 6 and 150 be power	
Module	Full Bridge SCM5B38-01,-02,-05,-06,-07	Half Bridge SCM5B38-03,-04
Input Range Input Bias Current	$\begin{array}{c} \pm 10 mV \text{ to } \pm 100 mV \\ \pm 0.3 nA \end{array}$	*
Normal	50MΩ	*
Overload	40kΩ	*
Signal Input Protection Continuous Transient	240Vrms max ANSI/IEEE C37.90.1	*
Excitation Output (-02, -04, -05, -07)	+10V ±3mV 3000 to 10k0	*
Excitation Output (-01, -03, -06)	+3.333V ±2mV	*
Excitation Load Regulation	±5ppm/mA	*
Half Bridge Voltage Level (-04)	±15ppm/°C NA	+5V ±1mV
Half Bridge Voltage Level (-03) Isolated Excitation Protection	NA	+1.667V ±1mV
Continuous Transient	240Vrms max ANSI/IEEE C37 90 1	*
CMV, Input to Output	1500///	*
Transient	ANSI/IEEE C37.90.1	*
CMR (50 or 60Hz) NMR (-3dB at 10kHz)	100dB 120dB per Decade above 10kHz	*
Accuracy ⁽²⁾	±0.03% Span	*
Stability		÷
Output Offset	±1μν/°C ±40μV/°C	*
Gain	±25ppm of Reading/°C	*
Input, 0.1 to 10Hz Output, 100kHz	0.4µVrms 10mVp-p	2µVrms
Bandwidth, –3dB Rise Time, 10 to 90% Span	10kHz 35µs	*
Settling Time, to 0.1%	250µs	*
Output Range Output Resistance	See Ordering Information 50Ω	*
Output Protection Output Selection Time	Continuous Short to Ground 6us at C = 0 to 2000pF	*
(to ±1mV of V _{out}) Output Current Limit	+8mA	*
Output Enable Control	0.01/	
Min Logic "1"	+0.8V +2.4V	*
Max Logic "1" Input Current "0,1"	+36V 0.5μΑ	*
Power Supply Voltage	+5VDC ±5%	*
	70mA No Exc. Load	÷
Power Supply Sensitivity Mechanical Dimensions	±2μV/% RTI ⁽³⁾ 2 28″ x 2 26″ x 0 60″	*
(h)(w)(d)	(58mm x 57mm x 15mm)	
Environmental Operating Temperature Range	–40°C to +85°C	*
Storage Temperature Range Relative Humidity	-40°C to +85°C 0 to 95% Noncondensing	*
Emissions EN61000-6-4	ISM, Group 1	*
		â
Radiated, Conducted Immunity EN61000-6-2	Class A ISM, Group 1	*
Radiated, Conducted Immunity EN61000-6-2 RF ESD_EET	Class A ISM, Group 1 Performance A ±0.5% Span Error	* * *

Ordering Information

Model (10kHz)	Type Bridge Input	Input Range	Excitation	Sens.	Output Range [†]
SCM5B38-01	Full	-10mV to +10mV	+3.333V	3mV/V	1, 2
SCM5B38-02	Full	-30mV to +30mV	+10.0V	3mV/V	1, 2
SCM5B38-03	Half	-10mV to +10mV	+3.333V	3mV/V	1, 2
SCM5B38-04	Half	-30mV to +30mV	+10.0V	3mV/V	1, 2
SCM5B38-05	Full	-20mV to +20mV	+10.0V	2mV/V	1, 2
SCM5B38-06	Full	- 33.3mV to +33.3mV	+3.333V	10mV/V	1, 2
SCM5B38-07	Full	-100mV to +100mV	+10.0V	10mV/V	1, 2

[†]Output Ranges Available

Output Range	Part No. Suffix	Example
1. –5V to +5V	NONE	SCM5B38-01
210V to +10V	D	SCM5B38-01D



Figure 2: Full Bridge Connet ion







i y NOTES:

* Same as -01, -02, -05, -06, -07 modules.
(1) Strain element. (2) Includes linearity, hysteresis and repeatability. (3) RTI = Referenced to input.

Visit our website www.dataforth.com

23

©1995-2017 Dataforth Corporation, All Rights Reserved ISO9001:2008-Registered QMS

Accessories for SCM5B Analog Modules

► Features

- 1-, 2-, 8-, 16-Position Backpanels
- Panel or DIN Rail Mounting Options
- 19-Inch Mounting Rack For Backpanels
- Multiplexed and Non-Multiplexed Backpanels

SCMPB01

16-Position Analog I/O Backpanel, Non-Multiplexed

Description

The SCMPB01 16-channel backpanel (Figure 1) can accept any of the SCM5B analog modules in any mixture. It can be mounted on the SCMXRK-002 19-inch metal rack. The SCMPB01 has 16 non-addressable analog I/O signal channels which provides each module with it's own analog bus. The module output switch is continuously "on" when using this backpanel and all sixteen module outputs are simultaneously accessible to high-speed data acquisition (ADC) boards. A set of inter-channel bridge jumpers permits connecting an input module's output to an output module's input, providing two levels of isolation. A temperature sensor is mounted on each channel to provide cold junction compensation for thermocouple input modules (see Figure 2 for schematic). Field connections are terminated with four screw terminals at each module site. Use system interface cable SCMXCA004-XX for connection to the host system.

- Interface Cables
- Module Evaluation Board
- Cable-to-Screw-Terminal Interface Board
- Power Supplies



Specifications

Operating Temperature Relative Humidity	-40°C to +85°C 95% Noncondensing
Interface Connector: Field System	high density screw clamp, 14 AWG max 26-pin, male header connector
Isolation: Input-to-Output Channel-to-Channel	1500Vrms continuous, max 1500Vrms continuous, max



Figure 1: SCMPB01 Analog I/O Backpanel

SCM5B

SCM5B



Figure 2: SCMPB01 Schematic

Visit our website www.dataforth.com

Electrical

P1 and P2 Connector

Connection to the host system is made at connectors P1 and P2. These connectors are electrically equivalent. Two connectors are provided to allow both analog input and analog output from host systems having individual input and output connectors.

Adjacent Channel Jumpers

Adjacent channels may be connected together to provide an isolated output signal from an isolated input module, providing two levels of 1500V isolation. This capability is provided with the 15 jumpers labeled JP1 through JP15 on headers E1, E2, and E3. A simplified drawing of the SCMPB01 schematic for Channel 1 through 4 is shown in Figure 3.

Example: Assume an SCM5B30 input module is installed in Channel 0 position and an SCM5B39 output module is installed in Channel 1 position. If JP1 is installed, the output of Channel 0 is connected to the input of Channel 1, which provides two levels of 1500V isolation.



Figure 3: SCMPB01 Adjacent Channel Jumpers

Power

The SCMPB01 backpanel requires external +5VDC \pm 5% power. The chassis mounted SCMXPRE-003 or SCMXPRT-003 power supplies have adequate capacity to power any combination of modules.

Fusing

The SCMPB01 backpanel power is fuse protected through F1. This is a Littelfuse type 252007, 7 amp fuse. Zener diode DZ1 provides extra protection by clamping the input power voltage to +5.6V. If the input supply voltage connection is reversed, this zener diode will be forward biased and fuse F1 will be blown.

Grounding

Figure 4 details the optional ground jumper configuration available on the SCMPB01 backpanel. Jumpers J1, J3, and J4 are factory installed.

Jumper J1 connects the AGND shield wires (pins 3, 6, 9, 12, 15, 18, 21, and 24) to the backpanel signal ground. This provides a ground connection between the host system and backpanel. Jumper J1 is required if output modules (SCM5B39, SCM5B49) are used, or if there is no high impedance sense input (input low of a differential or pseudo-differential system) on the host measurement system.

Jumper J3 connects the SENSE line (pin 25) to the backpanel signal ground. If the host system has the capability, this allows measuring the SCMPB01 ground potential.

Ordering Information

Part Number	Description
SCMPB01	16-channel backpanel with standoffs for mounting.
SCMPB01-1	16-channel backpanel without cold junction compensation circuits and standoffs for mounting. Use when cost savings is desired and thermocouple input modules SCM5B37 and SCM5B47 will not be used.
SCMPB01-2	16-channel backpanel with DIN rail mounting option. The backpanel is mounted on a plate which is captured by the SCMXBExx DIN rail mounting elements. Shipped fully assembled.
SCMPB01-3	16-channel backpanel without cold junction compensation circuits and with DIN rail mounting option. Shipped fully assembled.

For proper operation of the output switch or track-and-hold circuit when using the SCMPB01/05 backpanels, a current path must exist between the host control logic power common and module I/O Common (module pin 19). This path can be established on the SCMPB01 via jumper J4. If this connection exists elsewhere in the system, jumper J4 should be removed since possible ground loops could exist. Other connections of power ground and signal ground usually occur at the A/D or D/A converter of the host measurement system. More information on grounding can be found in Application Note AN502.



Figure 4: SCMPB01 Grounding Diagram

If the connection of power common and AGND shield wires exist in the host measurement system, an optional resistive connection between AGND and the backpanel signal ground can be made via R_1 . R_1 can be as large as 10K ohms; 100 ohms is a recommended value. Jumper J2 can be used to connect the SENSE line to R_1 when this ground configuration is used.

For full protection against large electrical disturbances on the field-side of the SCM5B modules, a #10-32 ground stud is provided on the backpanel. An electrical connection between this ground stud and system ground should be provided with a large gauge wire of the shortest possible length. When this connection is made, a possible ground loop could result through the AGND shield wires and backpanel signal ground. If the application involves only input modules and a differential input is used by the host measurement system, J1 should be removed. Remember that J1 is required if output modules are used or if the host system does not have differential inputs.

For information call 800-444-7644

SCM5B

SCMPB02 16-Position Analog I/O Backpanel, Multiplexed

Description

The SCMPB02 16-channel backpanel (Figure 5) can accept any of the SCM5B analog modules in any mixture. It can be mounted on the SCMXRK-002 19-inch metal rack. The SCMPB02 has two analog buses; one for analog input and one for analog output. This two-bus configuration takes advantage of the switch controlled outputs on the input modules and the track-and-hold inputs on the output modules. A temperature sensor is mounted on each channel to provide cold junction compensation for thermocouple input modules (see Figure 6 for schematic). Field connections are terminated with four screw terminals at each module site. Up to four SCMPB02 backpanels may be daisy-chained.Use SCMXCA004-XX cable for daisy chaining and connecting to host computer.

Specifications

-40°C to +85°C 95% Noncondensing
high density screw clamp, 14 AWG max 26-pin, male header connector
1500Vrms continuous, max 1500Vrms continuous, max
0.8V 2.0V
0.1μA max at 25°C 1.0μA max –25°C to +85°C
51ns at 25°C 64ns at -25°C to +85°C 100ns at 25°C 126ns at -25°C to +85°C



Figure 5: SCMPB02 Analog I/O Backpanel



Figure 6: SCMPB02 Schematic

Electrical

P1 Connector

The 26 pin P1 and P2 connectors provide the signal interface between the SCMPB02 backpanel and the host measurement system. Two separate analog bus connections are provided; one for analog input signals and one for analog output signals. Two sets of six address lines and an enable pin allow input and output modules to be independently multiplexed onto their respective analog signal bus. R0 thru R5 and RD EN\ are used for input modules, and W0 thru W5 and WR EN\ are used for output modules.

Address Selection

The SCMPB02 backpanel has address decoding circuitry to allow multiplexing any combination of up to 16 input or output modules. Capability is also provided in the address decode circuitry to expand the system to 64 channels (four SCMPB02 backpanels) of multiplexed input or output. Jumpers on HD10 header, E1 and E2 group, select which set of 16 addresses are assigned to a particular backpanel. The E1 group assigns a set of 16 addresses for input modules, and the E2 group assigns a set of 16 addresses for output modules. The table below shows the correlation of jumper position to address range.

E1 Jumper Pos	E2 Jumper Pos	Address Range/Mode
4	4	0-15, STAND ALONE
3	3	48-63, EXPANDED
2	2	32-47, EXPANDED
1	1	16-31, EXPANDED
0	0	0-15, EXPANDED

To connect multiple SCMPB02 backpanels in this expanded configuration, use interconnect cable SCMXCA004-XX.

Modules with system output of $\pm 10V$ or 0-10V cannot be mixed with modules with system output of $\pm 5V$ or 0-5V within a given system.

Power

The SCMPB02 backpanel requires external +5VDC \pm 5% power. The chassis mounted SCMXPRE-003 or SCMXPRT-003 power supplies have adequate capacity to power any combination of modules.

Fusing

The SCMPB02 backpanel power is fuse protected through F1. This is a Littelfuse type 252007, 7 amp fuse. Zener diode DZ1 provides extra protection by clamping the input power voltage to +5.6V. If the input supply voltage connection is reversed, this zener diode will be forward biased and fuse F1 will be blown.

Grounding

Figure 7 below details the optional ground jumper configuration available on the SCMPB02 backpanel. Jumpers J1, J2, and J4 are factory installed.

Jumper J1 connects the SIG COM shield wires (pins 2, 5, and 6) to the backpanel signal ground. This provides a ground connection between the host system and backpanel. Jumper J1 is required if output modules (SCM5B39, SCM5B49) are used, or if there is no high impedance sense input (input low of a differential or pseudo-differential system) on the host measurement system.

Jumper J2 connects the SNS LO line (pin 4) to the backpanel signal ground. If the host system has the capability, this allows measuring the SCMPB02 ground potential.

Ordering Information

Part Number	Description
SCMPB02	16-channel backpanel with standoffs for mounting.
SCMPB02-1	16-channel backpanel without cold junction compensation circuits and standoffs for mounting. Use when cost savings is desired and thermocouple input modules SCM5B37 and SCM5B47 will not be used.
SCMPB02-2	16-channel backpanel with DIN rail mounting option. The backpanel is mounted on a plate which is captured by the SCMXBExx DIN rail mounting elements. Shipped fully assembled.
SCMPB02-3	16-channel backpanel without cold junction compensation circuits and with DIN rail mounting option. Shipped fully assembled.

For proper operation of the output switch or track-and-hold circuit when using the SCMPB02/06 backpanels, a current path must exist between the host control logic power common and module I/O Common (module pin 19). This path can be established on the SCMPB02 via jumper J4. If this connection exists elsewhere in the system, jumper J4 should be removed since possible ground loops could exist. Other connections of power ground and signal ground usually occur at the A/D or D/A converter of the host measurement system. More information on grounding can be found in Application Note AN502.

If the connection of power common and SIG COM shield wires exist in the host measurement system, a resistive connection between SIG COM and the backpanel signal ground can be made via R_1 , R_1 can be as large as 10K ohms; 100 ohms is a recommended value. Jumper J3 can be used to connect the SNS LO line to R_1 , when this ground configuration is used.

For full protection against large electrical disturbances on the field-side of the SCM5B modules, a #10-32 ground stud is provided on the backpanel. An electrical connection between this ground stud and system ground should be provided with a large gauge wire of the shortest possible length. When this connection is made, a possible ground loop could result through the SIG COM shield wires and backpanel signal ground. If the application involves only input modules and a differential input is used by the host measurement system, J1 should be removed. Remember that J1 is required if output modules are used or if the host system does not have differential inputs.



Figure 7: SCMPB02 Grounding Diagram

Description

Shipped fully assembled.

mounting hardware included.

Shipped fully assembled.

Ordering Information

Part Number

SCMPB03

SCMPB04

SCMPB04-1

SCMPB03-2

SCMPB03/SCMPB04

One/Two Position Analog I/O Backpanels

Description

The SCMPB03 and SCMPB04 are single and dual channel mounting panels for the SCM5B modules. Both are intended for DIN rail mounting.

See Figures 9 and 10 for wiring diagrams, Figure 11 for schematic.

The following accessories are required for mounting one SCMPB03/04 panel (Figure 8):

Qty	Model	Description
1 2	SCMXBEFE SCMXSE	Base element with snap foot Side element

The following accessories are required for mounting two or more SCMPB03/04 panels:

Qty	Model	Description
2	SCMXBEFE	Base element with snap foot
2	SCMXSE	Side element
(# panels)-2	SCMXBE	Base element without snap foot
(4 x (# panels))-4	SCMXVS	Connection pins

The following DIN rail styles are available. Specify length in meters (-XX)

SCMXRAIL1-XX	DIN EN 50022-35x7.5 (slotted steel)
SCMXRAIL2-XX	DIN EN 50035-G32 (slotted steel)
SCMXRAIL3-XX	DIN EN 50022-35x15 (slotted steel)

Specifications

Operating Temperature Relative Humidity	–40°C to +85°C 95% Noncondensing
Interface Connector: Field System	high density screw clamp, 14 AWG max high density screw clamp, 14 AWG max
Isolation: Input-to-Output Channel-to-Channel	1500Vrms continuous, max 1500Vrms continuous, max



SCMPB04-2

SCMPB04-3 Dual channel backpanel without cold junction compensation circuits and with DIN rail mounting hardware. Shipped fully assembled.

Single channel backpanel. No mounting hardware included.

Single channel backpanel with DIN rail mounting hardware.

Dual channel backpanel. No mounting hardware included.

Dual channel backpanel without cold junction compensation circuits. Use when cost savings is desired and thermocouple input modules SCM5B37 and SCMPB47 will not be used. No

Dual channel backpanel with DIN rail mounting hardware.









Figure 8: DIN Rail Mounting Elements





Figure 11: SCMPB03/SCMPB04/SCMPB07 Schematic

SCMPB05

8-Position Analog I/O Backpanel, Non-Multiplexed

Description

The SCMPB05 backpanel (Figure 12) can accept up to eight SCM5B analog input and/or output modules in any combination. It can be mounted on the SCMXRK-002 19-inch metal rack. A separate analog signal path is provided for each channel and each channel's signal is accessible at redundant 26-pin connectors. The module output switch is continuously "on" when using this backpanel and all eight module outputs are simultaneously accessible to high-speed data acquistion (ADC) boards.

On-board jumpers permit paralleling two SCMPB05 boards to form a SCMPB01 equivalent. An additional set of inter-channel bridge jumpers permits connecting an input module's output to an output module's input, providing two levels of isolation (Figures 12, 13).

Jumpers on the SCMPB05 permit user selection of low (i.e. channels 0-7) or high (i.e. channels 8-15) addresses.

A temperature sensor mounted on each channel provides cold junction compensation for thermocouple input modules (see Fig. 13 for schematic). Field connections are terminated with four screw terminals at each module site. Use system interface cable SCMXCA004-XX for connection to the host system.

Specifications

Operating Temperature Relative Humidity	-40°C to +85°C 95% Noncondensing	
Interface Connector: Field System	high density screw clamp, 14 AWG max 26-pin, male header connector	
Isolation: Input-to-Output Channel-to-Channel	1500Vrms continuous, max 1500Vrms continuous, max	

Ordering Information

Part Number	Description
SCMPB05	8-channel backpanel with standoffs for mounting.
SCMPB05-1	8-channel backpanel without cold junction compensation circuits and standoffs for mounting. Use when cost savings is desired and thermocouple input modules SCM5B37 and SCM5B47 will not be used.
SCMPB05-2	8-channel backpanel with DIN rail mounting option. The backpanel is mounted on a plate which is captured by the SCMXBExx DIN rail mounting elements. Shipped fully assembled.
SCMPB05-3	8-channel backpanel without cold junction compensation circuits and with DIN rail mounting option. Shipped fully assembled.

Electrical

Address Selection

Module addresses may be selected as low (channels 0-7) or high (channels 8-15) using the sets of 3 pins labeled J5 through J12. Place a jumper over the two pins closest to the ribbon cable connectors, P1 and P2, to select a low address (factory configuration) or over the two pins furthest from the ribbon cable connectors, P1 and P2, to select a high address.

Adjacent Channel Jumper

Adjacent channels may be connected together to provide an isolated output signal from an isolated input module, providing two levels of 1500V isolation. This capability is provided with the seven jumpers labeled JP1–JP7. See page 57 for an example.

Refer to page 50 for additional notes on the P1 and P2 connectors, power requirements, fusing and grounding issues.



Figure 12: SCMPB05 Analog I/O Backpanel

SCM5B



Figure 13: SCMPB05 Schematic

SCMPB06 8-Position Analog I/O Backpanel, Multiplexed

Description

The SCMPB06 backpanel (Figure 14) can accept up to eight SCM5B modules in any combination. It can be mounted on the SCMXRK-00219-inch metal rack. The SCMPB06 has two analog buses; one for analog input and one for analog output. This two-bus configuration takes advantage of the switch controlled outputs on the input modules and the track-and-hold inputs on the output modules. A temperature sensor is mounted on each channel to provide cold junction compensation for thermocouple input modules (see Figure 15 for schematic). Field connections are terminated with four screw terminals at each module site. Up to eight SCMPB06 backpanels may be daisy-chained. Use SCMXCA004-XX cable for daisy chaining and connecting to host computer.

Jumpers on the SCMPB06 permit user selection of low (i.e. channels 0-7) or high (i.e. channels 8-15) addresses.

Electrical

Address Selection

Module read and write addresses may be selected as low (channels 0-7) or high (channels 8-15) using the four sets of 3 position jumpers labeled J5 through J8. Place a jumper over the two pins furthest from the field I/O termination blocks on all four sets to select a low address (factory configuration) or over the two pins closest to the field I/O termination blocks on all four sets to select a high address.

The SCMPB06 backpanel has address decoding circuitry to allow multiplexing any combination of up to 8 input or output modules. Capability is also provided in the address decode circuitry to expand the system to 64 channels (eight SCMPB06 backpanels) of multiplexed input or output. Jumpers select which set of 16 addresses are assigned to a particular backpanel. The Read Address group assigns a set of 16 addresses for input modules. The table on the next page shows the correlation of jumper position to address range. Refer to page 53 for additional notes on the P1 and P4 connectors, power requirements, fusing, and grounding issues.

Modules with system output of $\pm 10V$ or 0-10V cannot be mixed with modules with system output of $\pm 5V$ or 0-5V within a given system.

Ordering Information

Part Number	Description
SCMPB06	8-channel backpanel with standoffs for mounting.
SCMPB06-1	8-channel backpanel without cold junction compensation circuits and standoffs for mounting. Use when cost savings is desired and thermocouple input modules SCM5B37 and SCM5B47 will not be used.
SCMPB06-2	8-channel backpanel with DIN rail mounting option. The backpanel is mounted on a plate which is captured by the SCMXBExx DIN rail mounting elements. Shipped fully assembled.
SCMPB06-3	8-channel backpanel without cold junction compensation circuits and with DIN rail mounting option. Shipped fully assembled.

Specifications

Operating Temperature Relative Humidity	-40°C to +85°C 95% Noncondensing
Interface Connector: Field System	high density screw clamp, 14 AWG max 26-pin, male header connector
Isolation: Input-to-Output Channel-to-Channel	1500Vrms continuous, max 1500Vrms continuous, max
Address Input Logic Levels: Max Logic "0" Min Logic "1"	0.8V 2.0V
I, Input Current, "0" or "1"	0.1μA max at 25°C 1.0μA max –25°C to +85°C
RD EN\ or WR EN\ Signal Delay from Connector P1 to Channels 0-7 Standalone (address 0-7) Expanded (address 8-63)	51ns at 25°C, 64ns at –25°C to +85°C 100ns at 25°C, 126ns at –25°C to +85°C



Figure 14: SCMPB06 Analog I/O Backpanel

Address Selection Jumpers

Read Write High/Low	
Address Address Channel Address Jumper (P2) Jumper (P3) (J5,J6,J7,J8) Address Rat	ange
1 6 L 0-7 Stand 1 6 H 8-15 Stand 2 7 L 48-55 Expan 2 7 H 56-63 Expan 3 8 L 32-39 Expan 4 9 L 16-23 Expan 4 9 H 24-31 Expan 5 10 L 0-7 Expan 5 10 H 8-15 Expan	d Alone d Alone nded nded nded nded nded nded nded n



Figure 15: SCMPB06 Schematic

SCMPB07 8-Position Backpanel, High Density

Description

The SCMPB07 8-channel high-density backpanel can accept any of the SCM5B analog modules in any mixture. Its overall width is 5.5 inches (139.7mm) versus 10 inches (254mm) for the SCMPB05 and SCMPB06 8-channel backpanels. Separate analog signal paths are provided for each channel. Each channel provides four high-density screw terminals for field connections and two high-density screw terminals for host system connection. It also provides a jumper on each channel to optionally connect or isolate each module's I/O common from other channel's I/O common and/or power common (Figure 16).

See Figure 11 on page 55 for schematic.

SCMPB07 and SCMPB07-1 can be upgraded to DIN rail mounting. The following accessories are required for mounting one SCMPB07 or one SCMPB07-1 backpanel (for a visual example, reference SCMPB03/SCMPB04 page 54, Figure 8):

Qty	Model	Description
2	SCMXBEFE	Base element with snap foot
2	SCMXSE	Side element
2	SCMXBE	Base element without snap foot
12	SCMXVS	Connection pins

Ordering Information

Part Number	Description	
SCMPB07	8-channel backpanel. No mounting hardware included.	
SCMPB07-1	8-channel backpanel without cold junction compensation circuits. Use when cost savings is desired and thermocouple input modules SCM5B37 and SCMPB47 will not be used.	
SCMPB07-2 Shipped	8-channel backpanel with DIN rail mounting hardware. fully assembled.	
SCMPB07-3	8-channel backpanel without cold junction compensation circuits and with DIN rail mounting hardware. Shipped fully assembled.	

Specifications

Operating Temperature Relative Humidity	–40°C to +85°C 95% Noncondensing
Interface Connector: Field System	high density screw clamp, 14 AWG max high density screw clamp, 14 AWG max
Isolation: Input-to-Output Channel-to-Channel	1500Vrms continuous, max 1500Vrms continuous, max



Figure 16: SCMPB07 Analog I/O Backpanel

60

For information call 800-444-7644

SCM5B

SCMXEV Analog Module Evaluation Board

Description

The SCMXEV is a single channel board with a test socket for SCM5B module evaluation (Figure 17). All signal input/output, control, and power connections are connected to terminal blocks for ease of user access. A cold junction temperature sensor circuit is included for evaluation of thermocouple modules (see Figure 18 for schematic).

The SCMXEV is mechanically compatible with DIN rail mounting. The following accessories are required for mounting one SCMXEV board (for a visual example, reference SCMPB03/SCMPB04 page 54, Figure 8):

Qty	Model	Description
2	SCMXBEFE	Base element with snap foot
2	SCMXSE	Side element
4	SCMXVS	Connection pins

Two jumpers are provided for customer use. The first, J1, provides a current path between +5V Power Common (module pin 16) and I/O Common (module pin 19). A path must exist between the host control logic power common and module I/O Common for proper operation of the module output switch or track-and-hold circuit. If this connection exists elsewhere in the system, jumper J1 should be removed since possible ground loops could exist. Other connections of power ground and signal ground usually occur at the A/D or D/A converter of the host measurement system.

Jumper J2 is used in the cold junction compensation circuit. If it is installed, the compensation circuit is enabled and will provide the proper compensation voltage to correct for the thermoelectric effect at the +In and –In screw terminals.



Figure 17: SCMXEV Evaluation Board Dimensions and Pin Layout

If an external simulation voltage is desired for cold junction compensation, J2 should be removed. The external voltage is applied at the sockets labled CJC+ and CJC-. An external voltage of 510.0mV corresponds to an ambient temperature of +25 °C. The transfer function of the onboard compensation circuit is $V_{CJC} = 0.510 - 0.0025(T-25)V$.



Figure 18: SCMXEV Evaluation Board Schematic

SCMXCA004-01, - 02

Interface Cable

Description

SCMXCA004-XX

System interface cable for the SCMPB01/02/05/06 backpanels. This is a 26 conductor ribbon cable with a mass-terminated socket connector installed on each end. It can be ordered in lengths of 1m and 2m; -xx denotes required length in meters (see Figure 19).



Figure 19: SCMXCA004-XX System Interface Cable

SCMXRK-002 19-Inch Metal Mounting Rack

Description

The SCMXRK-002 is a 19-inch metal rack for mounting the SCMPB01/02/05/06, SCM7BP04/08/16, SCMVAS-PB8/16 and isoLynx® SLX200-xx backpanels. It also provides capability to mount the SCMXPRT-001, SCMXPRE-001, SCMXPRT-003 or SCMXPRE-003 power supplies, and the SCMXIF interface board (see Figure 21 for dimensions)



Figure 21: SCMXRK-002 Analog Rack Dimensions

62

For information call 800-444-7644

SCMXIF (-DIN)

Universal Interface Board

Description

The SCMXIF is a universal interface board which converts a 26-pin ribbon cable input to 26 screw terminals for discrete wire. It can be mounted on the back of the SCMXRK-002 mounting rack (SCMXIF) or on a DIN rail (SCMXIF-DIN). Required mounting hardware is included. Use SCMXCA004-XX cable (see Figure 20 for dimensions).



Figure 20: SCMXIF Universal Interface Board Dimensions

Isolated Analog Signal Conditioning Products

SCM5B

SCMXCJC

Encapsulated Cold Junction Compensation

Description

The SCMXC IC is the identical circuit used on the SCMPB01/02/03/04/05/06/07 backpanels except it is packaged as a component for use in customer designed mounting boards (Figure 22). When interfaced to an SCM5B37 or 47 module the transfer function of the voltage across the +SEN and -SEN pins is $V_{cuc} = 0.510$ -0.0025(T-25)V.

Specifications

Accuracy +25°C +5°C to +45°C -40°C to +85°C

±0.25°C ±0.5°C +1.25°C

SCM5BPT

Pass Thru Module

Description

The SCM5BPT is a pass-through module used to establish a direct connection between an input signal and the SCM5B series backplane analog bus. It has unity gain and no isolation. It accepts up to ±10V input and provides up to ±10V output.

SCM5BPT-1367

Pass Thru Module with Switch

Description

The SCM5BPT-1367 is a pass-through module used to establish a direct connection between an input signal and the SCM5B series backplane analog bus. It has unity gain, no isolation, and a logic controlled output switch which allows sharing of a common analog bus with other SCM5B modules. It accepts up to ±10V input and provides up to ±10V output. Resettable fuses and overvoltage protection circuitry protect computer-side electronics.

SCMXJP-003

Jumper Strap

Description

Package of 10 jumpers for connecting adjacent input/output modules on the SCMPB01 backpanel. This connection is made if it is desired to direct the output of any input module to the input of an adjacent output module. The jumpers can also be used for configuring I/O addresses on the SCMPB02 backpanel.

SCMXFS-003, -004

Fuse

Description

Package of 10 fuses for use on the SCMPBxx backpanels. This is a series fuse in the five volt power line. It provides protection against inadvertent reverse connection of five volt power or overvoltage.





SCMXR1



Current Conversion Resistor

Description

CE

CE

A precision 20Q, 0.1%, 10ppm/°C resistor used with the SCM5B32 current input module or SCM5B42 two-wire transmitter interface module (Figure 23). Sockets are provided on the SCMPB01/02/03/04/05/06/07 and SCMXEV backpanels to allow installation of this resistor. One SCMXR1 is shipped with each SCM5B32 or SCM5B42 module.



Figure 23: SCMXR1 Physical Dimensions

Ordering Information

Part Number	Description	
SCMXFS-003	4A fuse. Use for SCMPB05/06/07, SCMVAS-PB8, -PB16.	
SCMXFS-004	7A fuse. Use for SCMPB01/02.	

(U)

SCM5B-PROTO

Breadboard Kit

Description

The SCM5B-PROTO breadboard kit was designed to allow users to incorporate their own module functions using an SCM5B format. The kit includes a pc board

designed for breadboard circuits, a module case, header and mounting screw. Contact the factory for additional information.

1.378

SCMXRAIL1-XX, SCMXRAIL2-XX, SCMXRAIL3-XX

DIN Rail

Description

Three styles of DIN rail are available. Specify length (-xx) in meters when ordering, -01 for 1 meter or -02 for 2 meter.



SCMXPRT-001/D, SCMXPRE-001/D

Power Supplies

Specifications Typical* at T_=+25°C

Description

The SCMXPRT-001/D and SCMXPRE-001/D encapsulated power supplies are available in 120VAC or 220VAC input voltage ranges and provide 5VDC outputs suitable for all SCM5B modules. They are designed to mount on the SCMXRK-002 metal rack or DIN rail EN 50022-35x7.5 (D versions). The supplies are UL-recognized. Their compact size and low weight are ideal for high-density applications (see Figure 25).

Module SCMXPRT-001/D SCMXPRE-001/D Input Voltage Range, 105-125VAC 200-240VAC 47Hz to 63Hz 5VDC Output Voltage 5VDC Output Current, +50°C 1A 1A (derate 2.5%/°C above +50°C) -25°C to +71°C -25°C to +71°C **Operating Temperature** Dielectric Withstand V 2500Vrms 2500Vrms (Input to Ground) ±0.05% ±0.05% Line Regulation Load Regulation ±0.15% ±0.15% 2mVrms Output Ripple, max 2mVrms **Overvoltage Protection** 6.2V 6.2V 1.25 lbs (567g) 1.25 lbs (567g) Weight

NOTES

64

* Contact factory or your local Dataforth sales office for maximum values. Supplies are UL recognized, File No. E65890.



Figure 25: SCMXPRT-001/D and SCMXPRE-001/D Physical Dimensions

SCM5B

SCMXPRT-003, SCMXPRE-003

Power Supplies

Description

The SCMXPRT/E-003 Linear Power Supplies are available in 120VAC or 220VAC input. They have sufficient output current capacity to supply any combination of SCM5B modules. The SCMXRK-002 metal rack provides mounting capability for the SCMXPRT/E-003 power supplies (see Figure 26).

Specifications Typical* at T_A=+25°C

Module	SCMXPRT-003	SCMXPRE-003
Input Voltage Range, 47Hz to 63Hz	104-132VAC	207-265VAC
Output Voltage	5VDC ±1%	5VDC ±1%
Output Current (at +70°C)	3A	3A
Output Current (at +50°C)	6A	6A
Operating Temp	0 to +70°C	0 to +70°C
Dielectric Withstand Voltage (input to ground)	3750VAC	3750VAC
Line Regulation (10% line change)	±0.05%	±0.05%
Load Regulation (50% load change)	±0.05%	±0.05%
Output Ripple (max)	5mVp-p	5mVp-p
Overvoltage Protection (factory set)	6.2V ±0.4V	6.2V ±0.4V

NOTES: * Contact factory or your local Dataforth sales office for maximum values

Both supplies are tested and certified by TUV to VDE 0806 and IEC 380. They are UL recognized (File Number E55974) and CSA Certified (CSA File Number LR38879).

PWR-4505 25W Single Output Industrial DIN Rail Switching Power Supply

Specifications Typical* at T_A=+25°C

Input Frequency Input Current Inrush Current Efficiency	85 to 264VAC, 120 to 370VDC 47 to 63Hz 1.5A/115VAC, 0.75A/230VAC Cold start 30A/115VAC, 60A/230VAC 72%
Output Voltage & Current Rating Temperature Coefficient Ripple Voltage	5V, 5A ±0.03%/°C 100mVp-p
Overload Protection Over Voltage Protection Over Temperature Protection	105 to 150% rated output power 5.75 to 6.75V 135°C detect on heatsink of power transistor
Dielectric Strength	Between input and output terminals: 3kV, 1 minute Between input and FG: 1.5kV, 1 minute Between output and FG: 0.5kV, 1 minute
Insulation Resistance	Between input and output terminals/input and FG/ output and FG: 100M $\Omega/500VDC$
Operating Temperature Storage Temperature Relative Humidity	-10°C to +50°C -20°C to +85°C 10 to 95%
Mechanical Dimensions (I)(w)(h)	3.66" x 3.07" x 2.24" (93mm x 78mm x 57mm)
Terminal Screw	M3

NOTES

* Contact factory or your local Dataforth sales office for maximum values



Figure 26: SCMXPRT-003/SCMXPRE-003

 \bigcap



Physical Dimensions

Features

- Universal AC Input (85 to 264VAC)
- DC Compatible Input (120 to 370VDC)
- · Protections: Short Circuit, Overload, Over Voltage, Over Temperature
- Mounts on DIN Rail TS-35/7.5 & 15
- · Approvals: UL, CUL, TUV, CB, CE
- CE Compliant, UL 508 Listed
- TUV EN60950-1 Approved
- Compliant with EMC Directive EN50082-2
- · LED Indicator for Power On





Terminal Pin No. Assignment